Intelligent pump monitoring and alarm notifications sent to your smart device anywhere in the world.

- Free app download
- Cloud-based system designed exclusively by Liberty Pumps
- No service or subscription fees (message and data rates may apply)
- · Works through your home's wireless router
- · Connect using simple BlinkUp™ technology
- Apple® iOS and Android® compatible
- One NightEye® app can support multiple devices/installations (separate control/alarm unit required for each installation)





800.543.2550 F 585.494.1839

7000 Apple Tree Ave Bergen, NY 14416 libertypumps.com



Model ALM-PK-EYE Puddle Sensor (For floor level water sensina)

Model ALM-P1-EYE Compact snap-on sensor float fits small pits with no interference

Model ALM-2-EYE Standard wide-angle float (for sewage applications)



Patent: See www.libertypumps.com/patents

MODEL	Float Style	Float Cord Length	Weight lbs.
ALM-P1-EYE	Compact snap-on	10'	2
ALM-2-EYE	Wide-angle	20'	4
ALM-2-1-EYE	Wide-angle	10'	3
ALM-PK-EYE	Puddle Sensor	50'	3

WATCH INSTALLATION VIDEO



the property of their respective owners and not property of Liberty Pumps.



Wireless Enabled Pump Alarm

ALWAYS WATCHING



Alarm Features

- NEMA 1, indoor rated
- · 120 volt operation with 9-volt battery backup
- · 86 dB audible alarm
- Super bright red LED alarm ring
- Green power on LED
- Low battery LED
- Low battery warning
- Automatic reset
- Wi-Fi LED
- Silence or test alarm manually or through your smart device
- Two switch styles available wide angle float or compact snap-on float (fits 1-1/4" and 1-1/2" pipe) (snap-on float not recommended for sewage applications)
- Auxiliary contacts for connection to other home security systems
- Device will run up to 12 hours on 9-volt battery with alarm active, up to 7 days in standby mode

App Features

- · Apple® iOS and Android® compatible
- Free download on Google® Play Store or the App Store
- · Cloud-based system technology
- Get immediate notification from your smart device of alarm activation - anywhere in the world
- Sends via text, email or push notification up to 4 different address/phone numbers
- Low basement temperature notification (user defines temperature level for warning)
- Silence or test your alarm remotely from your smart device
- One NightEye® app can control multiple devices (separate alarm/control units required)
- Loss of Wi-Fi notification (utilizes smart wireless monitoring to prevent nuisance notifications)

